KRAIT Technologies

CWduino KT-004

May 2022

Rev: 1.2 ENG

Compact CW transmitter fully compatible with Arduino Uno board 500 mW of RF output power at 5 VDC, 2000 mW at 9 VDC Keyer input to build a semi-automatic key Available in three band assemblies: 80 m, 40 m and 20 m

Features

- Highly integrated CW transmitter compatible with Arduino Uno board
- Class-E topology for high efficiency
- HF band coverage: 80, 40 and 20 m (depends on version)
- Built-in 2nd harmonic notch filter to meet CFR requirements (-43 dBc)
- 500 mW RF output power from 5 VDC Arduino's power supply rail
- 2000 mW RF output power at 9 VDC
- Keyer input connector (mini-jack)
- Transmitter keying available from pin PD4 (IOL group)
- · Precise frequency adjustment via trimmer
- Equipped with SMA connector for size critical applications
- Equipped with ISP connector (2x3 pin header)
- · Most components are THT for easy assembly

Mechanical Characteristics

- Fully mechanical and electrical compliance with Arduino Uno™ board
- Double-layer PCB
- Compact design: 68 × 54 x 12 mm

Application

- · Automatic keyer with integrated TX stage
- · Part of Arduino's controlled beacon
- Board for experiments with class E amplifier
- Experimental CW transmitter controlled from Arduino
- · Battery supplied experimental TX module
- Part of a portable CW transceiver

General description

The KT-004 CWduino is a fully integrated CW transmitter fully compatible with Arduino[™] Uno platform. CWduino is built as a highly efficient class E transmitter. Installed key input (minijack) allows to build a semi-automatic key. In that case one of the microcontroller's output can key the transmitter.

Three MOSFETs connected in parallel help to achieve low Rdson at low voltage (5 VDC) operation. If the Arduino Uno module is supplied from an external voltage source it allows to increase the RF output power up to 2000 mW at 9 VDC.

To keep the circuit simple there are no additional safety circuits for overvoltage and overcurrent condition. There is a large power loss margin on three transistors that can dissipate possible power losses under mismatch conditions.

Basic code examples for the Arduino environment can be downloaded:

http://www.krait-technologies.com/cwduino_examples.zip



FIGURE 1. Assembled CWduino KT-004 board

Circuit description

The Class-E amplifier (invented in 1964) is a highly efficient tuned switching power amplifier used at radio frequencies. [1] It uses a single-pole switching element and a tuned reactive network between the switch and the load. The circuit obtains high efficiency by only operating the switching element at points of zero current (on to off switching) or zero voltage (off to on switching) which minimizes power lost in the switch, even when the switching time of the devices is long compared to the frequency of operation. In Class-E, the output network values are chosen in such way that output capacitance is part of a total resonant circuit. [2]

Basic circuit topology is presented in the Fig. 2. It consists of three specific and one optional parts:

1) DC-feed choke (L1) connected to active switch (Q)

2) external capacitance (C1) connected parallel to MOSFETs drain-source junction

3) band-pass filter (L2-C2), which gives also impedance transformation

4) second harmonic notch filter (C3-C4-C5-L3) helps to strongly suppress harmonic content (not explicitly required, but desired to keep the second harmonic low according to CFR standard)



CWduino is only intended for use by licensed operators.

Local oscillator is built using 74ACT00 logic gates. ACT series has 24 mA output current capability which efficiently control MOSFETs gates. BS170 transistors were chosen because of very low value of input capacitance Coss (17 pF) which can be easily driven using a logic gate. Special version of logic gate IC (ACT series) was chosen because of 24 mA output current capability which can be directly used to control MOSFETs gate circuits. The adjustable bias circuit helps to set the optimal operation point of the transistors. The switches are driven with a \approx 50% duty cycle.

The local VCO is made using a crystal oscillator connected to one of the NAND gate. The output frequency can be adjusted with the trimmer.

The board is equipped with an input for a telegraph key: straight or paddle. It supports single and paddle keys. Note that Arduino's pin 2 is INT0 and pin 3 is INT1. It allows to realize the reading of CW key state as external interrupts to simplify code. Similarly, the control output (CW_TX) is controlled via pin 4 which is linked to hardware Timer 0.

The JP1 connector allows you to program the Arduino[™] Uno board via a 2x3 pin connector.

The capacitors used in the resonant circuits are NP0 (C0G) components which are super stability and have no aging effects.

The number of SMT pads on the board is greater than necessary. This allows for easy parallel connection of multiple capacitors during experiments. Note that each capacitor in Fig.2 has four pads on the board.

► To keep circuit simplicity the board has no additional OVP or OVC protection, because the power dissipated in the transistors will be safely dissipated on three transistors. Voltage margin is also provided. However, it is not recommended to run the amplifier with the disconnected load or in high mismatch condition. The optimal operation point of the amplifier is 50R RF load.

References:

[1] Ewing G.D., "High-Efficiency Radio-Frequency Power Amplifiers", Oregon State University, submitted in April, 1964.

[2] Sokal. N.O. "Class-E RF Power Amplifiers", QEX 2001, 204, 9-20.

Absolute Maximum Ratings

 Maximum Input Voltage:
 9V

 Maximum Output Power @ 50R @ 5V:
 500 mW (+27 dBm)

 Maximum Output Power @ 50R @ 9V:
 2000 mW (+33 dBm)

 Power Dissipation @ Pi_max @ 50R:
 0.6 W

 Operating Temperature Range:
 -45°C to +65°C

 Lead Temperature (Soldering 10 sec):
 +300°C

► Operating CWduino from 12.0 V results in 60 V peak voltage on the MOSFETs transitors and P_{indicent} = 4 W when running amplifier at 50R load. This voltage value is "Absolute Maximum Voltage" for BS170 transistor. Any load mismatch condition will cause their destruction!

Assembly procedure

It is highly recommended to start assembly from the smallest components (SMT IC and capacitors), then THT resistors and then install ferrite cores with windings. All types of connectors should be installed last.

Assembly variants

Note that CWduino kit can be assembled in a few variants depends on the ordered version.

If AVR microcontroller will be used to create key signal for transmitter stage do not assembly R3, C1.

If the CW paddle key plus semi-automatic code in Arduino board will be used assembly R1, R2 resistors and do not assembly R3, C1. Instead install R5.

If the CW straight key will be used install R2, R3, C1. Do not install R5.

Ferrite core winding procedure

If the next module (a shield board) will be stacked over CWduino it is required to assembly the ferrite cores in a horizontal position to meet the limit of height to the next board.

► It is a good practice to spread windings over a whole toroidal ferrite core.

►► If possible, measure the inductance of the coils to run amplifier at the optimal point. You can use VNA to measure coil's inductance at proper frequency.

Installing connectors

The CWduino layout has been designed in such a way that the two types connectors can be mounted interchangeably:

SMA type (X3) or

BNC type (X2) [optional]

Insulation consideration

▶ Pay attention for a required distance to the next stacked shield board (if exist). Put an additional insulator to avoid a short circuit.

Startup procedure

Connect two passive probes between points:

CH1 – D-S point to GND CH2 – RF_OUT to GND

Use plastic trimmers during adjusting output frequency (CT1) and bias voltage (PR1). Optimum D-S voltage waveform is shown in the Fig. 3. The center of the position of the PR1 potentiometer is a good starting point. Measure the input current by comparing it to the output voltage (indirectly RF output power). Note that if the output power does not not rise, if you turn the PR1 clockwise, it means you have set the correct BIAS voltage.

Final check

Connect dummy load (50R) to CWduino output. Connect a passive probe to points: RF_OUT and GND. Turn on the output power. Set FFT analysis on an oscilloscope. Check levels of non-fundamental harmonics.

47 CFR Part 97.307(d) specifies the limits. Below 30 MHz, all spurious emissions including harmonics must be suppressed 43 dB below the primary signal; from 30-225 MHz, it's 60 dB.



	TIGURATION	S	
PIN CONNECTIONS		PIN CO	NNECTIONS
ARDUINO standard	Function on CWduino	ARDUINO standard	Function on CWRduino
_	_	SCL	N.C.
_	_	● SDA	N.C.
_	_	AREF	N.C.
_	_	GND	GND (ISP)
N.C.	N.C.		SCK (ISP)
IOREF	N.C.		MISO (ISP)
/RESET	Reset (ISP)		MOSI (ISP)
+3V3	N.C.		N.C.
+5V	+5V (ISP)		N.C.
GND	GND (ISP)		N.C.
GND	GND (ISP)		N.C.
+Vin	+Vin		N.C.
A0	N.C.		N.C.
A1	N.C.		сw_тх
A2	N.C.		PADDLE DASI
A3	N.C.		PADDLE DOT
A4	N.C.		N.C.
A5	N.C.	0 (RX)	N.C.

FIGURE 7. Descriptive layer of CWduino (KT-004 board)

Electrical characteristics _____

Г

Input DC voltage [V]	Output RF voltage @ 50R load [Vrms]	Output power @ 50R load [W]
5.0	5.00	0.50
6.0	6.65	0.88
7.0	7.83	1.23
8.0	9.00	1.62
9.0	9.96	1.98
10.0*	11.8	2.42
11.0*	12.9	2.88
12.0*	14.2	3.92

*) Operating CWduino at an input voltage > 9,0 VDC will destroy transistors in mismatch condition. Given for a reference only.

				DADT	
No.	DESIGNATOR	DESCRIPTION	QTY	NUMBER	VALUE
1	X1	Mini-jack THT angle connector	1		
2	X2 X3	SMA THT angle female connector BNC THT angle female connector (optional; not included)	1 0	-	-
3	R1, R2, R3, R5	THT, 0,125 W, 47k	4		
4	R4	THT, 0,125 W, 1M	1		
5	R6	THT, shunt 0R	1		
6	C2, C3	THT, 20pF	2		
7	C1, C4, C6, C7, C8, C9	THT, 10nF, 35V, ceramic	6		
8	C5	1uF, 35V, THT electrolytic capacitor	1		
9	Q1, Q2, Q3	THT, MOSFET transistor	3	BS170	
10	CT1	5-30pF THT, trimmer	1		
11	IC1	4 x NAND gates, SO-14 package	1	74ACT00D	
12	PR1	THT, 10k, potentiometer	1		
13		Arduino Uno connectors: 1x6 pins, 2x8 pins, 1x10 pins	4		
14		1x4 goldpin	1		
15	JP1	2x3 goldpin	1		
16	Enamel wire	AWG #28	0,6 m		

80 m version:

► For experiments and future kit variants, there are several pads of capacitors connected in parallel to make easier to precisely combine the required capacities.

No.	DESIGNATOR	DESCRIPTION	QTY	PART NUMBER	VALUE
8	QZ1	Crystal quartz THT, low profile, 3.579545 MHz	1		
11	L1	35.49 uH (11 turns); grayish ferrite core	1	FT37-43	
12	L2	2.37 uH (21 turns); ferrite core painted red	1	T37-2 core	
13	L3	0.88 uH (11 turns); ferrite core painted red	1	T37-2 core	
14	C10, C11, C12, C13	1 x 560 pF (one component mounted in one of the four pads)	1	560pF 0805 NP0	
15	C14, C15, C16, C17	3 x 560 pF (three components mounted in three of the four pads)	3	560pF 0805 NP0	
16	C18, C19, C20, C21	3 x 560 pF (three components mounted in three of the four pads)	3	560pF 0805 NP0	
17	C22, C23, C24, C25	1 x 560 pF (one components mounted in one of the four pads)	1	560pF 0805 NP0	
18	C26, C27, C28, C29	3 x 560 pF (three components mounted in three of the four pads)	3	560pF 0805 NP0	

40 m version: TBD 20 m version: TBD

CW Key _____

When connecting a straight key use tip and sleeve. When connecting a paddle use tip, ring and sleeve.

▶ Make sure the voltage retained by the keyer is less than 0.4 V when the key is ON.



FIGURE 8. Connecting CW key

CW bandplan on HF bands _____

Table 5. CW mode bandplan					
Base band	Frequency range for CW mode	Center frequency for CW QRP operation			
80m	3500 – 3580 kHz	3555 kHz			
40m	7000 – 7040 kHz	7030 kHz			
20m	14000 – 14070 kHz	14060 kHz			

Mechanical Details _____

The CWduino shield is fully compatible with the Arduino Uno[™] footprint. If ferrite cores are assembled flat it is possible to install a next shield above, according to Arduino Uno™ standard.

Board dimensions: 68 x 54 x 12 mm (measured without pins length below the board) PCB specification: FR 4, double sided, 35 um layers, HAL

Ordering Information _____

Description	Version	Ordering Code	QTY
Printed circuit board only	PCB	KT-004B	1
Kit for self assembly (components for 80m, SMA output connector, crystal 3.579545 MHz)	Kit	KT-004K/80	1
Kit for self assembly (components for 40m, SMA output connector, crystal 7.023 MHz)	Kit	KT-004K/40	1
Kit for self assembly (components for 20m, SMA output connector, crystal 14.060 MHz)	Kit	KT-004K/20	1

KRAIT Technologies 29/166 Stefana Batorego Street 02-591 Warsaw Poland	An information furnished by KRAIT Technologies is believed to be accurate and reliable. However, no responsibility is assumed by KRAIT Technologies for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice.		
EUROPE	Trademarks and registered trademarks are the property of their respective owners. Arduino Uno™ is registered trademark of Arduino LLC.		
www.krait-technologies.com	CE Z Compliant		
©2022 KRAIT Technologies. All rights reserved.	Made in POLAND	E1:472	
www.krait-technologies.com	6/6	CWduino (KT-004)	